

Amendments to the Claims

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (Currently amended) A position-control stage comprising a bed, a turntable supported for rotation on the bed through a rolling-contact bearing, a linear motor moving the turntable relatively to the bed in a circular direction, and an encoder monitoring a relative position of the turntable to the bed;

wherein the linear motor is comprised of armature windings at a primary side and field magnets at a secondary side;

wherein the armature windings are each made of a three-phase coreless coil where winding turns are wound in a form of flat rectangular loop, are circularly arranged on a disc surface of the bed along a preselected curvature, and lie in radial juxtaposition in circumferential direction;

wherein the field magnets are made in a flat shape and arranged underneath the turntable in such a pattern lying radially on a disc surface of the preselected curvature in opposition to the armature windings, with their unlike poles alternating in polarity along a circular direction; and

wherein the linear motor in minimum unit is comprised of three armature windings and five field magnets; and

wherein the field magnets are disposed on the disc surface of the turntable throughout an overall circular direction while the armature windings lie on the disc surface of the bed over a preselected area in the circular direction in case where the position-control stage requires large circular angle in relative turning of the turntable to the

bed.

2-3. (Canceled)

4. (Previously presented) A position-control stage constructed as recited in claim 1, wherein there is provided a pair of the linear motors made in minimum unit in case where the position-control stage requires less circular angle in relative turning of the turntable to the bed.

5. (Canceled)

6. (previously presented) A position-control stage comprising a bed, a turntable supported for rotation on the bed through a rolling-contact bearing, a linear motor moving the turntable relatively to the bed in a circular direction, and an encoder monitoring a relative position of the turntable to the bed;

wherein the linear motor is comprised of armature windings at a primary side and field magnets at a secondary side;

wherein the armature windings are each made of a three-phase coreless coil where winding turns are wound in a form of flat rectangular loop, are circularly arranged on a disc surface of the bed along a preselected curvature, and lie in radial juxtaposition in circumferential direction;

wherein the field magnets are made in a flat shape and arranged underneath the turntable in such a pattern lying radially on a disc surface of the preselected curvature in opposition to the armature windings, with their unlike poles alternating in polarity along a circular direction; and

wherein the field magnets fit in a circular recess cut in an underside of the turntable, and the armature windings lie circularly on a coil support that fits in a circular recess sunken below a top surface of the bed.

7. (Currently amended) A position-control stage comprising a bed, a turntable supported for rotation on the bed through a rolling-contact bearing, a linear motor moving the turntable relatively to the bed in a circular direction, and an encoder monitoring a relative position of the turntable to the bed;

wherein the linear motor is comprised of armature windings at a primary side and field magnets at a secondary side;

wherein the armature windings are each made of a three-phase coreless coil where winding turns are wound in a form of flat rectangular loop, are circularly arranged on a disc surface of the bed along a preselected curvature, and lie in radial juxtaposition in circumferential direction;

wherein the field magnets are made in a flat shape and arranged underneath the turntable in such a pattern lying radially on a disc surface of the preselected curvature in opposition to the armature windings, with their unlike poles alternating in polarity along a circular direction; ~~and~~

wherein a linear encoder to monitor any turning position of the turntable relative to the bed is comprised of an optical linear scale surrounding around an outside periphery of the turntable, and a sensor arranged on the bed; and

wherein an origin mark is affixed to the underside of the turntable in opposition to the sensor of the bed at a preselected position in the circular direction.

8. (Canceled)

9. (previously presented) A position-control stage comprising a bed, a turntable supported for rotation on the bed through a rolling-contact bearing, a linear motor moving the turntable relatively to the bed in a circular direction, and an encoder monitoring a relative position of the turntable to the bed;

wherein the linear motor is comprised of armature windings at a primary side and field magnets at a secondary side;

wherein the armature windings are each made of a three-phase coreless coil where winding turns are wound in a form of flat rectangular loop, are circularly arranged on a disc surface of the bed along a preselected curvature, and lie in radial juxtaposition in circumferential direction;

wherein the field magnets are made in a flat shape and arranged underneath the turntable in such a pattern lying radially on a disc surface of the preselected curvature in opposition to the armature windings, with their unlike poles alternating in polarity along a circular direction; and

wherein a stopper extends below the underside of the turntable while another stopper extends above the top surface of the bed, so that the turntable stops turning after the stopper has come into abutment against the another stopper, and a before-the-origin sensor and a limit sensor are installed short of the another stopper on the bed to detect when the stopper on the turntable reaches the sensors.

10. (previously presented) A position-control stage comprising a bed, a turntable supported for rotation on the bed through a rolling-contact bearing, a linear motor moving the turntable relatively to the bed in a circular direction, and an encoder monitoring a relative position of the turntable to the bed;

wherein the linear motor is comprised of armature windings at a primary side and field magnets at a secondary side;

wherein the armature windings are each made of a three-phase coreless coil where winding turns are wound in a form of flat rectangular loop, are circularly arranged on a disc surface of the bed along a preselected curvature, and lie in radial juxtaposition in circumferential direction; wherein the field magnets are made in a flat shape and arranged underneath the turntable in such a pattern lying radially on a disc surface of the preselected curvature in opposition to the armature windings, with their unlike poles alternating in polarity along a circular direction; and

wherein the turntable is made at a center thereof with an opening for looking into the interior to form a circular support where the turntable is supported for rotation on another circular support of the bed through the rolling-contact bearing.

11. (Canceled)

12. (previously presented) A position-control stage constructed as recited in claim 9, wherein there are provided a power line to convey electric power to the armature windings, a sensor line to signal to the sensors on the bed, and a signal line to receive any signal from the limit sensor and the before-the-origin sensor, and the lines are all clumped together through a cord cover attached to the bed.